TF Card Upgrade Operation Instruction

First, decompression the software to the folder:



Software _for_PNDT7021_20121219.img IMG 文件

PhoenixCardV306 20120302

1. Insert an empty TF card with TFcard reader to you computer.

有可移动存储的设备	
DISK (G:)	
2. Open the phoenixCardV306_20120302 to find	了 PhoenixCard.exe PhoenixCard Microsoft 基础 and run it. Please
PhoenixCard 3.06	
Card and Inage	
DiskDeck disk -	
Log File c. uncoments and Settings comministrator (ADM 001/0414 _ Log Fine _ Log Fine _ Log File _	
© Product 🗌 User Bata	
C Stertup ! Bata Path	
Purn Format to Normal Clear Info Nalp Exit	
Rate	
3 PhoenixCard Microsoft 基础 PhoenixCard Microsoft 基础	can automatically detect the TE
I	mg File C:\Documents
card. Then click "Img File	to import
"softare_for_PNDT7021_20121219.img	¹⁷ .
Burn	
4. Cilck and wait for	several minutes until the dialog
box show burn finished". Please refer to	o following picture.

🖣 PhoenixCard 3.06	🏹 PhoenixCard 3.06 📃 🗆 🗙
-Card and Inage DiskCheck disk [0.\ ▼ Ing File [:\Uncomments and Settings\Administrator\原面)谢建文件夹\Settware _for_FBUTT021_20121219 ing	- Card and Inage DiskElack disk 0./ Ing File C./Documents and Settings/Administrator/桌面明建文件夹/Software_for_FNDTTO21_20121219.ing
Frite Hold Ø Frohet User Data C Stertep /	Write Hole Ø Brobact Ø Bror Data Startup / Data Path
Burn Fernat to Hermal Clear Info Help Exit Bate	Purn Format to Hermal Clear Info Help Exit Rate
Option Formatting the cord 开始政策 优容基果一部分规定写成 优级基果干部分规定写成 LWEL规定写成 DootLoader1起写完成 DootLoader1起写完成	Option ● (PatipleStatic ● (PatipleStatic ● (PatipleStatic ● (PatipleStatic ● (PatipleStatic ●

5.Make sure you MID tablet have enough battery power for upgrading, power device off, and then insert the TF card, and power device on, then device will upgrade by itself.



6. After upgrading finish, the device will shutdown automatically. Please remove TF card before power it on.